

(19) World Intellectual Property Organization
International Bureau(43) International Publication Date
20 September 2001 (20.09.2001)

PCT

(10) International Publication Number
WO 01/69568 A1(51) International Patent Classification: **G08C 19/12**,
19/00, H04L 17/02, G05B 19/02, H04N 5/44, H04B 10/00

(21) International Application Number: PCT/US00/06401

(22) International Filing Date: 13 March 2000 (13.03.2000)

(25) Filing Language: English

(26) Publication Language: English


(71) Applicant and

(72) Inventor: **MATTHEWS, Carl, G.** [US/US]; 3544 Bell,
Kansas City, MO 64111 (US).(74) Agent: **LUEBBERING, Thomas, B.**; Hovey, Williams,
Timmons & Collins, Suite 400, 2405 Grand Boulevard,
Kansas City, MO 64108 (US).(81) Designated States (national): AE, AL, AM, AT, AU, AZ,
BA, BB, BG, BR, BY, CA, CH, CN, CR, CU, CZ, DE, DK,DM, DZ, EE, ES, FI, GB, GD, GE, GH, GM, HR, HU, ID,
IL, IN, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR, LS, LT,
LU, LV, MA, MD, MG, MK, MN, MW, MX, NO, NZ, PL,
PT, RO, RU, SD, SE, SG, SI, SK, SL, TJ, TM, TR, TT, TZ,
UA, UG, UZ, VN, YU, ZA, ZW.(84) Designated States (regional): ARIPO patent (GH, GM,
KE, LS, MW, SD, SI, SZ, TZ, UG, ZW), Eurasian patent
(AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European patent
(AT, BE, CH, CY, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU,
MC, NL, PT, SE), OAPI patent (BF, BJ, CF, CG, CI, CM,
GA, GN, GW, ML, MR, NE, SN, TD, TG).**Published:**

— with international search report

For two-letter codes and other abbreviations, refer to the "Guidance Notes on Codes and Abbreviations" appearing at the beginning of each regular issue of the PCT Gazette.

(54) Title: CHANNEL NUMBER ORGANIZER



(57) Abstract: A channel number organizer for a remote control (Fig. 3) enables the user of a television remote control (10) using the channel up and down functions to define a scrolling loop of selected channels as a result of the available channels. By entering a loop designation, scrolling is enabled on the television (12) only for those channels included in the subset, thereby skipping unwanted channels, and positioning channel numbers with or without regard to numerical sequence order.

- 1 -

CHANNEL NUMBER ORGANIZER

RELATED APPLICATIONS

5

Not applicable.

FEDERALLY SPONSORED RESEARCH OR DEVELOPMENT

10

Not applicable.

MICROFICHE APPENDIX

15

Not applicable.

BACKGROUND OF THE INVENTION

20

1. FIELD OF THE INVENTION

The present invention relates to the field of television channel selection control. More particularly, the invention is concerned with a channel organizer system that enables the user of a television remote control using the channel up and channel down functions to define a scrolling loop of selected channels as a subset of the available channels. By entering a loop designation, scrolling is enabled only for those channels included in the subset, thereby skipping unwanted channels.

30

2. DESCRIPTION OF THE PRIOR ART

A typical television remote control includes keys for channel up and channel down functions. By activating one of these keys, the television scrolls through the various channels in sequence.

35

Some cable television systems provide thirty or more channels and satellite systems often provide more than a hundred channels. Scrolling through this many

-2-

channels can be time-consuming and inefficient for a viewer who wishes to scroll through the channels in order to find a program of interest.

5 SUMMARY OF THE INVENTION

The present invention solves the prior art problem discussed above and provides a distinct advance in the state of the art. In particular, the channel organizer hereof enables a viewer to define those channels
10 of interest as a subset of the available channels and scroll through this subset in a time efficient manner.

The preferred channel organizer apparatus of the present invention includes a memory device coupled with a controller responsive to keypad entries on a remote
15 control. In the preferred embodiment, the apparatus is incorporated as part of the remote control.

In operation according to the preferred method of the present invention, a loop designation is received by way of a keypad and represents a designated scrolling
20 loop, with loop data representative thereof stored in the memory device. Also, channel designations are received by way of the keypad and represent a subset of the total number of channels available, with channel data representative thereof also stored in the memory device in
25 association with the loop data.

In response to entry of the loop designation, the loop and channel data are retrieved from the memory device. Scrolling is enabled using the channel up and down keys only for those channels included in the subset
30 thereby skipping those unwanted channels outside the subset. In preferred forms, a plurality of different scrolling loops may be defined each with a customized

-3-

subset of the available channels. Other preferred aspects of the present invention are disclosed herein.

BRIEF DESCRIPTION OF THE DRAWINGS

5 Figure 1 is a schematic representation of a television remote control incorporating the preferred channel organizer apparatus of the present invention in use for controlling the channel selection of a television;

10 Fig. 2 is an electrical block diagram of the remote control of Fig. 1; and

 Fig. 3 is a plan view of the remote control and keypad of Fig. 2.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

15 Figure 1 illustrates remote control 10 in accordance with the present invention shown in use with a receiver in the nature of television 12. It will be appreciated that the present invention encompasses receivers of other types operable for presenting a
20 plurality of channels including a video cassette recorder (VCR), cable television reception unit, satellite television reception unit, computer, and radio or the like.

 Referring to Fig. 2, preferred remote control 10
25 includes conventional microcontroller 14 having an internal read-only-memory (ROM) containing programming for implementing the operation thereof in accordance with the present invention. Remote control 10 also includes a nonvolatile, random-access-memory (RAM) 16 as the
30 preferred memory device, conventional battery power supply 18, conventional infrared (IR) output device 20 operable for sending coded IR control signals to television 12, and keypad 22. Microcontroller 14 is responsive to entries on

-4-

keypad 22 according to the programming for storing data as needed in RAM 16 and for providing output signals by way of output device 20 to control television 12 including channel selection thereon.

5 Fig. 3 illustrates remote control 10 and keypad 22. As shown, keypad 22 includes conventional keys for channel UP and channel DOWN, PREVIOUS (previous channel), volume UP and volume DOWN, numerics (0 through 9), the ENTER function and ON/OFF. In accordance with the present
10 invention, keypad 22 also includes additional keys for use in implementing the preferred method hereof in cooperation with the conventional keys. As discussed further herein, these additional keys include LOOP, ADD, DELETE, DISPLAY/EDIT, SELECT, MOVE, COPY, RESET and UNDO.

15 In order to set up a loop, the user presses LOOP, a numeric key corresponding to an unused loop designation such as "2" and then presses ENTER. Microcontroller 14 responds by storing loop data representative of the "loop 2" designation in RAM 16.

20 The user then selects those channels to be included in loop 2. This is accomplished by pressing ADD, the numeric key or keys corresponding to the channel number such as "4" and "8" as the channel designation for channel 48, and then ENTER. In response, microcontroller
25 14 stores channel data representative of the channel designation "48" in RAM 16 in association with the loop data for loop 2. This process is repeated to add additional channels such as the six channels (CH) of loop 2 illustrated on the screen of television 12 in Fig. 1.
30 In this example, the six channels comprise a subset of all of the available channels which make up the primary set.

 As an alternative, the channel UP and channel DOWN keys can be used to add channels to the loop. The

-5-

user presses ADD then UP or DOWN to scroll through a plurality of channels and then presses ENTER. This adds all of those channels that were scrolled to the channel loop. As another technique, pressing ADD then ENTER adds the current channel to the loop.

With a loop defined such as loop 2, scrolling is enabled for the channel UP and DOWN keys only for those channels in the subset such as the six channels illustrated in Fig. 1. Thus, if the displayed channel is channel 48, pressing channel UP results in a scroll to the next channel in the subset which is channel 17 while skipping all of the channels inbetween. Continued activation of channel UP continues the scrolling through channels 74, 4, 32, 12, and back to 48 in a closed loop. Activation of the channel DOWN initiates the scrolling through these channels in reverse order. As this procedure indicates, the channels in a given subset can be arranged in any desired order, without regard to numerical sequence. The procedure for deleting channels is the same as that for adding a channel except for pressing the DELETE key.

The procedure described above is repeated to define other loops. After a loop is defined, pressing LOOP followed by numeric keys corresponding to the loop number activates this loop. That is, microcontroller 14 responds to these entries on keypad 22 and retrieves the corresponding loop data and associated channel data from RAM 16. Scrolling is enabled using channel UP and DOWN only for those channels in the subset represented by the channel data and scrolling skips those channels outside the subset.

The DISPLAY/EDIT key initiates the display and edit functions. Pressing DISPLAY/EDIT followed by LOOP

-6-

and a channel number causes display of the loop information as illustrated in Fig. 1. Specifically, this initiates display of the loop number and the channels included in the subset for that loop. DISPLAY/EDIT also
5 functions as an escape key to void changes made before the ENTER key is pressed.

The SELECT key is used after MOVE or COPY to mark the start and end of a group of channel numbers to be moved or copied. If otherwise pressed, the display is
10 replaced by the current channel number highlighted by a cursor.

The MOVE key moves a selected channel number section to a new location within the current loop. This function is initiated by pressing MOVE, SELECT, and then
15 channel UP or DOWN to scroll through a channel group to be moved. SELECT is pressed and then channel UP or DOWN to move to the location in the loop for insertion of this channel group. Pressing ENTER enters the channel group in the new location. This channel group can be moved to a
20 different loop by pressing LOOP and the numerics for the loop number after the SELECT key.

The COPY function allows a group of channels to be copied to a new location in the same loop. The sequence is COPY, SELECT and channel UP or DOWN to scroll
25 through the channel numbers to be copied. The user then presses SELECT and channel UP or DOWN to move to the loop location for insertion. Pressing ENTER copies the selected channels to the new location in the loop. The channel group can be copied to a different loop by
30 pressing LOOP and the numerics for the loop number after SELECT.

RESET reloads the current loop with all available channel numbers in numerical order. This can be

-7-

useful when completely redefining a given loop. UNDO can be pressed to negate a channel deletion when using the DELETE function if activated before any other key is pressed.

5 In the preferred embodiment, the capacity of RAM 16 is sufficient for storing loop data and channel data for ten loops corresponding to numeric keys 0-9. It is preferred that loop "0" is the default loop always containing all of the available channels. That is, with
10 loop 0, the subset is coextensive with the primary set. With loop 0 as the designated loop, remote control 12 functions in the conventional mode allowing channel UP or DOWN to scroll through all of the available channels.

 This leaves nine loops available for custom use.
15 For example, each member of a household can have his or her own custom-defined loop with that person's favorite channels included in the associated subset. Also, loops can be defined for different types of channels. For example, one loop could include all of the sports channels
20 and another could contain the movie channels while still another contains the commercial broadcast network channels.

 Moreover, the ease of use of the ADD and DELETE functions allows a given loop to be revised on an ongoing
25 basis. For example, for a sports channel loop, channels can be deleted as a sporting event ends and others added as sporting events begin on these other channels.

 It will also be appreciated that the control functions can reside in the receiver rather than in the
30 remote control. For example, the preferred control apparatus including microcontroller 14 and RAM 16 could be present in television 12 instead of remote control 10. Most televisions include signal processing and memory

-8-

capabilities and the functions of the present invention could be readily and economically added. This would reduce the cost of the remote control.

Those skilled in the art will appreciate that
5 the present invention encompasses many other variations in the preferred embodiment described herein. Having thus described this embodiment, the following is claimed as new and desired to be secured by Letters Patent:

10

CLAIMS:

1. A method of controlling channel selection on a receiver operable for receiving and presenting a plurality of channels as a primary set of channels and responsive to control signals from a remote control for selection of a channel, the remote control being operable for transmitting the control signals in response to entries on a keypad including channel up and channel down entries for scrolling through a plurality of channels on the receiver, said method comprising the steps of:
- (a) by way of the keypad, receiving a loop designation representative of a scrolling loop and storing loop data representative thereof in a memory device;
 - (b) by way of the keypad, receiving channel designations representative of a subset of channels selected from said primary set and storing channel data representative thereof in association with said loop data in said memory device;
 - (c) in response to entry of said loop designation by way of said keypad, retrieving said loop data and associated channel data from said memory device and enabling scrolling on the receiver, in response to channel up and channel down entries on the keypad, only through those channels included in said subset and skipping those channels outside said subset; and
 - (d) repeating steps (a), (b) and (c) for a plurality of said scrolling loops.

-10-

2. The method as set forth in claim 1, steps (a) and (b) including the steps of storing said loop data and channel data in a memory device included within the remote control.

5

3. The method as set forth in claim 1 including the step of performing step (c) for a receiver as one of a television, VCR, cable television reception unit, satellite television reception unit, computer, and radio.

10

4. The method as set forth in claim 1 including the step of performing step (c) for a scrolling loop associated with a subset coextensive with said primary set.

15

5. The method as set forth in claim 1, the receiver including a display screen, said method further including the step of responding to a display entry on the keypad by displaying on the screen the loop designation and associated channel designations of channels included in said subset.

20

6. The method as set forth in claim 1 further including the step of responding to an add entry on the keypad by adding a selected channel to said subset.

25

7. The method as set forth in claim 1 further including the step of responding to a delete entry on the keypad by deleting a selected channel from said subset.

30

8. The method as set forth in claim 7 further including the step of responding to an undo entry on the keypad by negating the response to said delete entry.

-11-

9. The method as set forth in claim 1, further including the step of responding to a move entry on the keypad by moving selected ones of the channels to one of a different scrolling location within said subset and a
5 subset in a different scrolling loop.

10. The method as set forth in claim 1, further including the step of responding to a copy entry on the keypad by copying selected ones of the channel
10 designations to one of a different scrolling location within said subset and a subset in a different scrolling loop.

11. The method as set forth in claim 1, further
15 including the step of responding to a reset entry on the keypad by including all of the channels in said primary set in said subset.

12. The method as set forth in claim 1 further
20 including the step of performing steps (a)-(d) within the remote control.

-12-




13. A channel organizer apparatus for use with a receiver operable for receiving and presenting a plurality of channels as a primary set of channels and responsive to control signals from a remote control for selection of a channel, the remote control being operable for transmitting the control signals in response to entries on a keypad including channel up and channel down entries for scrolling through a plurality of channels on the receiver, said apparatus comprising:
- 5 a memory device; and
 - 10 a controller coupled with said memory device and including means responsive to entries on the keypad for
 - 15 storing loop data in said memory device representative of a designated scrolling loop in response to entry of a loop designation on the keypad of the remote control, and
 - 20 storing, in said memory device in association with said loop data, channel data representative of a subset of channels selected from said primary set in response to entry of channel designations on the keypad of the remote control,
 - 25 said controller including means for responding to entry of said loop designation by way of said keypad by retrieving said loop data and associated channel data from said memory device, and
 - 30 enabling scrolling on the receiver, in response to channel up and channel down entries on the keypad, only through those channels

-13-

included in said subset and skipping those
channels outside said subset,
said controller further including means for storing
loop data and associated channel data for a
5 plurality of said channel loops and associated
subsets of channels.

14. The apparatus as set forth in claim 13, said
controller and memory device being included as part of the
10 remote control.

1/1



INTERNATIONAL SEARCH REPORT

 International application No.
 PCT/US00/06401

A. CLASSIFICATION OF SUBJECT MATTER

IPC(7) : G08C 19/12, 19/00; H04L 17/02; G05B 19/02; H04N 5/44; H04B 10/00

US CL : 341/173, 176; 340/825.57, 825.72, 825.22; 348/734; 359/146

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

U.S. : 341/173, 176; 340/825.57, 825.72, 825.22; 348/734; 359/146

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practicable, search terms used)

EAST

search terms: favorite, channel, remote control, scan

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	US 5,414,426 A (O'DONNELL et al) 09 May 1995, entire document	1-14
X	US 5,481,251 A (BUYS et al) 02 January 1996, entire document	1-14
X	US 5,481,256 A (DARBEE et al) 02 January 1996, entire document	1-14

☐ Further documents are listed in the continuation of Box C.
 ☐ See patent family annex.

* Special categories of cited documents:	** later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention
A document defining the general state of the art which is not considered to be of particular relevance	*X* document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone
B earlier document published on or after the international filing date	*Y* document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art
L document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)	
O document referring to an oral disclosure, use, exhibition or other means	
P document published prior to the international filing date but later than the priority date claimed	*G* document member of the same patent family

Date of the actual completion of the international search

19 MAY 2000

Date of mailing of the international search report

03 OCT 2000

 Name and mailing address of the ISA/US
 Commissioner of Patents and Trademarks
 Box PCT
 Washington, D.C. 20231

Facsimile No. (703) 305-3230

Authorized officer

ALBERT WONG

Telephone No. (703) 305-3949